



5 Input Launch Amplifier BC84486

FEATURES:

- Adjustable SAT / Terrestrial gain and slope for all inputs
- DC passing between SAT inputs and outputs
- Application in 5-wire systems
- Sheet metal housing
- -30dB test ports
- Foxtel Approved IPL# F30850
- Indoor wall mounting
- Earthing terminal

MANUFACTURER (REF#)	Switch Master (HIAMP55)		
FOXTEL APPROVAL #	F30843		
MAXIMUM GAIN	FREQ	MAX	DESIGN
	Satellite	28dB (2GHz)	10-23dB
	Terrestrial	29dB (UHF)	10-24dB
GAIN ADJUSTMENT RANGE	Satellite	0-20dB	As required
	Terrestrial	0-20dB	As required
GAIN ADJUSTMENT ↻ = MAX GAIN CLOCKWISE			
OUTPUT LEVELS	FREQ	MAX	DERATED
	Satellite	112dBuV	105dBuV
	Terrestrial	110dBuV	104dBuV
SLOPE	Satellite	4-10dB	Set to MAX
	Terrestrial	4-10dB as required	
SLOPE ADJUSTMENT ↻ = MAX SLOPE CLOCKWISE			
OUTPUT TEST POINTS	5 ports x -30dB		
POWER PASS	Via PORTS	H1 & H2 outputs	
	Switchable	ON / OFF by S1	
	Current	Limit 2200mA MAX	
ACTUAL CURRENT TO POWER AMPLIFIER	With internal electronics "only"	Load 305mA	
CONNECTOR TYPE	F-Type Female		
DIMENSIONS	165 x 135 x 52 mm (L x W x H)		
PACKAGING	White Box with Label		
WHAT'S INCLUDED	• 1x 5 Outlet Amplifier • 2x Screws		
WARRANTY	1 Year		

FOR MORE INFORMATION:

☎ 1300 601 915 ✉ orders@bitek.com.au 🌐 www.bitek.com.au

DISTRIBUTED BY: **BITEK** BITEK PTY LTD

