





| MATERIALS | | |
|-----------|------------------------------------|--|
| 5 | Brass, Nickel plated Bead Flange | |
| 4 | Brass, Nickel plated body | |
| 3 | Plastic Insulator 3GHz POM Blue | |
| 2 | Beryllium Copper, gold plated Claw | |
| 1 | Brass, Nickel plated Pin | |



F-Type Female to F-Type Female Barrel Connector - 3GHz

05BCFF3 05BCFF3BK

White Black

FEATURES:

- · Supports digital broadband performance up to 3GHz
- Excellent signal quality with over 35dB return loss @1GHz
- Nickel-plated body resists corrosion for long-lasting reliability
- Gold-plated contacts provide strong signal flow and low resistance
- Beryllium copper connector ensures firm grip and consistent
- Precision-machined threads for secure and stable connections
- Easy plug-in design for quick installation Foxtel approved for trusted compatibility

| INSERT TYPE | F-Type |
|--------------------|-------------------------|
| INSERT CONNECTIONS | F-Type Female |
| COLOUR | White/Black |
| INSERT RATING | 3GHz Barrel |
| INSERTION LOSS | ≤0.5dB @1GHz |
| RETURN LOSS | >35dB @1GHz |
| INSERT STYLE | Digitek & Clipsal Style |
| MATERIALS | ABS Plastic |
| FOXTEL APPROVED | F Barrel F30468 |
| Rohs Compliant | Yes |
| PACKAGING | Poly Bag with Label |
| WARRANTY | 1 Year |
| | |

FOR MORE INFORMATION:

DISTRIBUTED BY: SITE SITES PTY LTD