



(11E109)



(11E116)



(11E130)



(11E124)



(11E127)

**1-Drop 5-1000MHz Right Angle Coupler
- 130dB RFI**

11E109	9dB
11E116	16dB
11E124	24dB
11E127	27dB
11E130	30dB

FEATURES:

- Designed for use in large distributed MATV systems
- Used to tap off the exact signal level required for each outlet/cable run
- 1-way configuration
- Five different signal variations
- Zinc diecast housing
- F-Type Female connectors for easy installation
- Includes power pass feature
- Power pass from input to output

SUB HEADER CATEGORY	Free-To-Air
COUPLER POINTS	1-Drop
FREQUENCY RANGE	5-1000MHz
TAP LOSS	11E109: 9dB
	11E116: 16dB
	11E124: 24dB
	11E127: 27dB
	11E130: 30dB
CONNECTION TYPE	F-Type Female
COUPLER VARIANT	Right Angle
PACKAGING	Single Piece
WHAT'S INCLUDED	• 1x 4-Drop Coupler
WARRANTY	1 Year

FOR MORE INFORMATION:

☎ 1300 601 915 ✉ orders@bitek.com.au 🌐 www.bitek.com.au

DISTRIBUTED BY: **BITEK PTY LTD**