



Self-Lock F-Type Connector (RG6 Quad) **12B6FSLQ**

FEATURES:

- No tools required — simply strip the cable and slide on the connector
- Self-locking teeth-ring grips cable firmly and prevents accidental removal
- Fast, simple installation for both professionals and DIY users
- Compact design (<23mm) allows easy use in tight spaces
- Durable nickel-plated brass construction for long service life and corrosion resistance
- Strong mechanical hold via 11mm (7/16") hex nut for secure, stable connection
- Low signal loss and excellent conductivity ensure superior performance
- Compatible with RG6 quad shield coaxial cable
- Reliable connection without compression or crimping tools
- Ideal indoor solution for audio/video and RF applications

PRODUCT TYPE	Self-Lock F-Type Connector
CONNECTOR TYPE	F-Type Male
CABLE TYPE	RG6/RG6 Quad Shield Coaxial Cable
TERMINATION TYPE	Self-Lock (No Tool Required)
MATERIAL	Nickel-Plated Brass
COLOUR	Silver
HEX NUT SIZE	11mm (7/16")
LENGTH	<23mm
FREQUENCY RANGE	5MHz - 3000MHz
RECOMMENDED STRIPPING TOOLS	Digitek 16A06 or 16A06A
OPERATING ENVIRONMENT	Indoor use only
PACKAGING	Single Piece or Bag of 100
WARRANTY	1 Year

FOR MORE INFORMATION:

☎ 1300 601 915 ✉ orders@bitek.com.au 🌐 www.bitek.com.au

DISTRIBUTED BY: **BITEK PTY LTD**